



Product Specification

- Emergency Call Station: Model 2100-852SE (Single element Strobe)
- Emergency Call Station: Model 2100-852DE (Dual element Strobe)

1.0 General Description

- 1.1 The Emergency Call Station shall be rectangular in appearance and made of steel construction 18 gauge thickness. The Call Station shall stand 39" high and be capable of being mounted flush or on a pole. The words "EMERGENCY TELEPHONE" with bright reflective lettering shall be located on the front and the words "EMERGENCY" on the sides. The Phone shall be compliant with the American with Disabilities Act and be powered with 110 volt or optional 12vdc or 24vdc. Line powered is not acceptable.
- 1.2 The Emergency communication component shall comply with the American with Disabilities Act. The Phone shall have the ability to be programmed with up to 5 emergency phone numbers. Upon activation of the emergency push button; a call will be automatically placed, the strobe shall instantaneously flash and any ancillary devices tied into the Phone will be activated until the call has been disconnected by the called party.

2.0 Construction

- 2.1 The Emergency Call Station shall be constructed of 18 gauge galvanized steel that is weatherproof, and manufactured with a weather and corrosion resistant finish.
- 2.2 The Emergency Call Station is to be 39" high, 10" wide and 8" deep with all components of its construction to be vandal resistant.
- 2.3 The Emergency Phone plate shall be made of 11 gauge stainless steel and is 13" inches high and 7" inches wide.
- 2.4 The Emergency Phone button shall be located on the Call Station and is to be located no more than 36" above ground level to ensure conformance with the ADA requirements.
- 2.5 Call Station must have a Braille faceplate located approx. 36" above ground level to ensure conformance with the ADA requirements.
- 2.6 The strobe shall be mounted within overall construction of unit enclosed within Plexiglas housing. Strobe will come fully assembled.





- 2.7 Phone electronics and most electrical connections must be housed in a Nema 4 enclosure within the Emergency Call Station.
- 2.8 Call Station shall have a rear access panel that is accessible by removing entire back panel via vandal resistant screws.
- 3.0 Mounting
 - 3.1 The Emergency Call Station is to be mounted on a flat wall surface or on a pole if the pole mounting bracket is being utilized.
- 4.0 Electrical
 - 4.1 The phone shall be powered by 110 VAC or optional 12vdc or 24vdc .
 - 4.2 Strobe shall be powered by 110 VAC or optional 12vdc or 24vdc .
 - 4.3 Electrical connections are to be made inside a Nema 4 enclosure or with water proof wire nuts provided by Rath Microtech.
- 5.0 Lights
 - 5.1 Strobe light shall be located at the top of the Emergency Call Station. The strobe shall be activated upon pushing of the emergency phone button. The strobe shall have an output of approx. 1,000,000 Candlepower and flash at a rate of a minimum of 70 times per minute.
 - 5.2 Single Element Strobe (Model 2100-847SE) Blue light flashes when phone is activated.
 - 5.3 Dual Element Strobe (Model 2100-847DE) Blue light is constantly on and Strobe flashes when phone is activated. If optional photocell is selected, unit must turn constant light on at dusk and off at dawn.
 - 5.4 Wide Area light (If Specified). The unit shall have a vandal resistant housing with capability of supporting a 100 watt CFL bulb.
- 6.0 Communications
 - 6.1 The unit shall have an ADA compliant and Vandal resistant speaker phone.





- 6.2 The Phone shall be a 1 push to talk phone. Once the button has been pushed, the phone will call programmed emergency numbers. The Phone must be capable of being programmed with up to 5 emergency numbers.
- 6.3 Phone shall have "Location Message" capability. Phone must have a minimum 18 second recordable message capability, programmable to play 1, 2 or 3 times. Phone shall notify called party of the location of the call upon being received at the Emergency dispatch center.
- 6.4 Phone shall be capable of allowing the called party to replay the location message (Location Message feature) if necessary to ensure an understanding of the location of phone tower.
- 6.5 Once call has been made (button pushed) the call can only be terminated by the called party.
- 6.6 Phone plate must have a red LED that will light up upon push of the button. The light shall be a solid color when the phone is activated, and will flash when call has been answered.
- 6.7 The speakerphone must be capable of being programmed and reprogrammed on-site and remotely.
- 6.8 Phone must have a built in phone line consolidator feature. Phones must be capable of sharing phone lines with up to 10 Rath Microtech SmartPhones if required by end user to reduce operational cost.
- 6.9 Line powered phones and Dip Switch programming are not acceptable.
- 6.10 Standard Phone features:
 - 6.10.1 Five number programming.
 - 6.10.2 Weatherproof speaker.
 - 6.10.3 Weatherproof microphone.
 - 6.10.4 Operating Temperature of between -40° F to +150° F (-40° to + 65° C)
 - 6.10.5 Programmable passwords.
 - 6.10.6 On-Site or Remote Programmable.
 - 6.10.7 Two output relays.
 - 6.10.8 EEPROM memory to protect programming.
 - 6.10.9 4 hour battery back-up in case of power failure.
 - 6.10.10 Adjustable speaker and microphones levels.





7.0 Finish

- 7.1 Unit shall be powder coated white with a weatherproof and corrosion resistant finish. End user must be capable of requesting custom colors .
- 7.2 Unit must be UV resistant.

8.0 Graphics

- 8.1 All wording shall be made of highly reflective vinyl lettering.
- 8.2 The Standard text like "EMERGENCY" shall be available in Blue with each letter to be a minimum of 3" in height.

9.0 Options

- 9.1 There shall be custom paint options for the Emergency Call Station.
- 9.2 A Camera control option must be available if requested.
- 9.3 A Wide area speaker system must be available if requested.
- 9.4 A Wide area lighting system must be available if requested.
- 9.5 System must allow for custom school or company 's logo on the tower similar to how the words "Emergency" is affixed.
- 9.6 System must allow for custom tower notification lettering in place of "Emergency" if requested.
- 9.7 Strobes must also be available in Red and Amber .

10.0 Warranty

The unit shall be warranted for a period of two years.

11.0 Manufacturer

The manufacturer shall be:
Rath
N56 W24720 North Corporate Circle
Sussex, WI 53089
866-850-8854
Website: www.rathsecurity.com

